

**FAXLAN CLIENT v3.0
INSTALLATION GUIDE
FOR WINDOWS XP**

Version 1.1
May 15th, 2003

TABLE OF CONTENTS

1. FAXLAN OVERVIEW	3
1.1 FAXLAN SYSTEM REQUIREMENTS.....	3
2. FAXLAN INSTALLATION PROCEDURE	4

1. FaxLAN Overview

Congratulations on your purchase of the FAXLAN system. FAXLAN is a piece of software that receives faxes on your PC workstation just like e-mail, and stores it on your PC. FAXLAN allows you to view received faxes on your monitor at your leisure, and only print out the ones you choose while deleting unwanted ones.

1.1 FaxLAN System Requirements

MicroEnergy Inc.'s FaxLAN v3.0 software requires a fax server, available at MicroEnergy Inc., connected to a fax line, as well as a local network connection from your PC to the fax server.

FaxLAN v3.0 software requirements include:


- One of the following Windows OS
 - Microsoft Windows 9x with Internet Explorer 5.5 SP2 Upgrade or higher
 - Microsoft Windows NT 4.0 with Internet Explorer 5.5 SP2 Upgrade or higher
 - Microsoft Windows Me
 - Microsoft Windows 2000 Professional
- Any version of Adobe Acrobat Reader. The latest version of Adobe Acrobat Reader can be downloaded for free at <http://www.adobe.com>.

The installation also requires the WinZip® utility. A free trial version is available for download at <http://www.winzip.com>.


2. FAXLAN Installation Procedure

“*FaxLan*” is designed to be professionally installed. If you are not familiar with computer hardware or software, please arrange a computer technician to install this program.


1. Download the installation files from
http://<FaxLAN server IP address>/install.zip.
2. Use WinZip® to unzip *install.zip* to the *C:\FaxLAN* directory. Create the directory in WinZip® if it does not already exist. The folder
3. Double click *C:\FaxLAN\Install\Step3\Setup.exe* and files will be installed automatically.



4. Double click "C:\FaxLAN\Faxlan.exe"




A Logon Dialog Box would then appear.




Please enter your user name and password and click **OK**. This will bring up FaxLAN client startup window. Choose Exit under the File Menu to quit FaxLAN.

5. Open Printer and Faxes folder in Control Panel. Click **Add a Printer** under Printer Tasks.




This will bring up the Add Printer Wizard. Click **Next**.

- The Add Printer Wizard will then ask you to choose whether you are installing a local or network printer. Choose local printer and disable the auto-detect checkbox.




Click **Next**.

- The Add Printer Wizard would then ask you to select the printer port. Choose **Create a new port**. For port type, choose **Redirected Port**.




Click **Next** and a dialog box will appear prompting you to enter the new port's name. Keep the name Windows chose for you and click **OK**. Click **Next** again.

- The Add Printer Wizard now asks you to install the printer driver software. Select **Apple** under Manufacturer, and **Apple LaserWriter 16/600 PS** under Printers.



Click **Next**.

- The Add Printer Wizard then asks you for the name of the printer. Type **FaxLAN** in the given data field. Choose **No** when it asks you whether you want to set this printer as the default printer.




The screenshot shows the 'Add Printer Wizard' dialog box with the title 'Add Printer Wizard' in a blue header. Below the header, the section is titled 'Name Your Printer' and includes the instruction 'You must assign a name to this printer.' A printer icon is visible in the top right corner. The main area contains the text: 'Type a name for this printer. Because some programs do not support printer and server name combinations of more than 31 characters, it is best to keep the name as short as possible.' Below this is a text input field labeled 'Printer name:' containing the text 'FaxLAN', which is circled in green. Underneath is the question 'Do you want to use this printer as the default printer?' with two radio button options: 'Yes' (unselected) and 'No' (selected), with a green arrow pointing to the 'No' option. At the bottom, there are three buttons: '< Back', 'Next >', and 'Cancel'.

Click **Next**.

10. The Add Printer Wizard then asks you whether you want to share this printer. Select **Do not share this printer**. Then click **Next**.


The Add Printer Wizard now asks if you want to print a test page. Choose **No**.



Click **Next**.

11. Then you would arrive at the last dialog box in the Add Printer Wizard. It will display the information you have just entered. Click **Finish**.


- Open up Printer and Faxes in the Control Panel. Right-click the FaxLAN printer and select **Properties**.



The printer properties dialog box will appear.

- Select the **Ports** tab and click on the **Configure Port** button.

- Under “Redirect this port to the program” data field, type **C:\FAXLAN\FAXLAN.EXE** or wherever you have placed the FaxLAN executable. Under the “Arguments for this program” type **faxlan**.




Click **OK**.

15. Select the **General** tab and click **Print Test Page**. If everything is successful, FaxLAN will automatically activate and the New Fax screen would appear.

If you would like to view the test page, click on **Save as PDF** in the Action Selection radio buttons. This will cause the fax recipient and cover page information to disappear and replace them with a file name data field. Type in **test** in the data field and click **Submit**. That will bring you to the PDF storage window.

Click on the view hyperlink on the entry with test in it to view the test page. The test page should look as follows.



The installation is now complete.